


**Data sheet**

page 1 of 2

**Infrared LED**
**EOLD-1720-015**

Rev. 02, 2017

Radiation	Type	Case
Infrared	InGaAs/InP, MQW	TO-46 with glass lens cap

 Dimensions (Unit:mm)	<b>Description:</b> High-power, high speed, narrow beam angle, high reliability
	<b>Applications:</b> Optical switches, optical communication, safety equipment, automation

**Maximum Ratings**
 $T_{amb}$ = 25°C, unless otherwise specified

Parameter	Test conditions	Symbol	Value	Unit
Forward current		I <sub>F</sub>	100	mA
Peak forward current (pulse)	t ≤ 50 μs, T = 100 μs	I <sub>FM</sub>	200	mA
Reverse voltage	I <sub>R</sub> =10 μA	I <sub>FM</sub>	5	V
Power dissipation		P <sub>D</sub>	100	mW
Operating temperature range		T <sub>amb</sub>	-20 to +85	°C
Storage temperature range		T <sub>stg</sub>	-30 to +100	°C
Lead soldering temperature	t < 5 s, 3 mm from case	T <sub>sld</sub>	260	°C
Junction temperature		T <sub>J</sub>	100	°C



We reserve the right to make changes to improve technical design and may do so without further notice. Parameters can vary in different applications. All operating parameters must be validated for each customer application by the customer.

**Data sheet**


page 2 of 2

Infrared LED**EOLD-1720-015**

Rev. 02, 2017

**Optical and Electrical Characteristics**
 $T_{amb} = 25^\circ\text{C}$ , unless otherwise specified

Parameter	Symbol	Conditions	Min	Typ	Max	Unit
Forward voltage	$I_F=20 \text{ mA}$	$V_F$		0.7	0.95	V
Forward voltage	$I_F=100 \text{ mA}$	$V_F$		0.9		V
Reverse voltage	$I_R=10 \mu\text{A}$	$V_R$	5			V
Radiant power	$I_F=20 \text{ mA}$	$\Phi_e$		1		mW
Radiant power	$I_F=100 \text{ mA}$	$\Phi_e$		4		mW
Peak wavelength	$I_F=20 \text{ mA}$	$\lambda_p$		1720		nm
FWHM	$I_F=20 \text{ mA}$	$\Delta\lambda_{0.5}$		130		nm
Viewing angle	$I_F=20 \text{ mA}$	$\phi$		6		deg.
Switching times	$I_F=20 \text{ mA}$	$t_r, t_f$		15		ns



Typical radiation pattern

Art. No. 430 052



We reserve the right to make changes to improve technical design and may do so without further notice. Parameters can vary in different applications. All operating parameters must be validated for each customer application by the customer.